# theMura S180-101 UP WH

Item no.: 2060655



# Presence and motion detectors Wall installation indoor

### Description

- Passive infra-red presence detector for wall installation
- Square detection area 170°, 14 x 17 m (238 m²)
- 1 channel light (Relay, 230 V) and 1 channel presence (Relay, floating for HVAC control)
- Fully or semi-automatic operation
- External button can be connected
- Adjustable brightness switching value, teach-in function
- Automatic calibration of brightness measurement
- Switch-on delay configurable
- Short-term presence
- Acoustic function
- Orientation light
- Configurable sensitivity
- External button can be connected
- Staircase light function
- Extension of detection area via master/slave switching
- Ready for immediate use due to factory presetting
- Remote operation with the Senda S, the Senda P, the Senda B
- Mixed light measurement suitable for the control of fluorescent, incandescent, halogen lamps and LEDs
- Integrated button (can be blocked)
- Product design by ID  $\ensuremath{\mathsf{AID}}$



#### Technical data

|                                | theMura S180-101 UP WH   |  |  |
|--------------------------------|--|--|--|
| Operating voltage              | 230 V AC   |  |  |
| Frequency                      | 50 - 60 Hz   |  |  |
| Installation height            | 0.8 - 1.2 m  |  |  |
| Installation type              | Wall installation  |  |  |
| Colour                         | White  |  |  |
| Switching output               | Light   Presence   |  |  |
| Power consumption              | ~0.4 W   |  |  |
| Light measurement              | Mixed light measurement  |  |  |
| Setting range brightness       | 5 - 3000 lx  |  |  |
| Light switch-off delay         | Impuls, 10 s - 60 min  |  |  |
| Lamp types                     | Incandescent/halogen lamps,<br>fluorescent lamps, Energy saving<br>lamps, LEDs |  |  |
| Incandescent/halogen lamp load | 2300 W   |  |  |


|                             | theMura S180-101 UP WH |  |
|-----------------------------|------------------------|--|
| Inrush current              | max. 600 A / 200 µs    |  |
| LED lamp < 2 W              | 40 W                   |  |
| LED lamp 2-8 W              | 450 W                  |  |
| LED lamp > 8 W              | 450 W                  |  |
| Switch-on delay presence    | 0 s - 10 min           |  |
| Presence switch-off delay   | 10 s - 120 min         |  |
| Switching capacity presence | 50 W/50 VA             |  |
| Type of connection          | Spring terminals       |  |
| Size of concealed housing   | 55 mm                  |  |
| Detection range             | 238 m² (14 x 17 m)     |  |
| Detection angle             | 170°                   |  |
| Ambient temperature         | -15°C 45°C             |  |
| Type of protection          | IP 20                  |  |

# theMura S180-101 UP WH

Item no.: 2060655





## Connection example



## Detection range for planning applications at a temperature of 21 °C

| Mounting height (A) | Head on to (R)       | Diagonally (t)       | Sitting (S) |
|---------------------|----------------------|----------------------|-------------|
| 1.2 m               | 120 m²   12 m x 10 m | 238 m²   14 m x 17 m |             |






# theMura S180-101 UP WH


Item no.: 2060655




#### Scale drawings


theMura S180-100 UP WH (2060650) + theMura S180-101 UP WH (2060655)








theMura S180-100 UP (2060750) + theMura S180-101 B UP (2060755)





#### Accessories

theSenda P Item no.: 9070910



theSenda S Item no.: 9070911



Surface frame LUXA 103-200 Item no.: 9070504



theSenda B Item no.: 9070985

